

MR9D Capkey Keypad Proximity Reader



- Sensor Touch keypad with built-in proximity reader
- Bi-color LED and buzzer indication
- Easy integration with different type of controller by using Wiegand output
- Operation Voltage : 12 VDC, 100mA
- Time for card verification: 100ms
- Transmit Distance: 10m
- Operating Temperature : -20°C ~ 70°C
- Humidity : 0% ~ 95%
- Dimension : 120 x 45 x 23 mm
- Weight: 200g
- Available in EM, Mifare, Mifare High Security format

Specification:

	EM	Mifare	Mifare High Security
Reader Output Format	Wiegand 26 bits	Wiegand 26/34 bits	Wiegand 26/34 bits
Keypad Output Format	Wiegand 4 bits output	Wiegand 4 bits output	Wiegand 4 bits output
Operation Frequency	125 KHz	13.56 MHz	13.56 MHz
Reading Range	30-80 mm	20-50 mm	30-80 mm
Sales Code	MR-CAPKEY-001	MR-CAPKEY-M01	MR-CAPKEY-M01-RW

MR9D Capkey Reader Wiring Diagram

